

PRODUCT DATA SHEET

HABOTEST®

HT108L True RMS Digital Pocket Multimeter



Features

- ❑ Multi-function: test AC/DC voltage, DC current, resistance, continuity, diode with lightweight and full-featured design.
- ❑ Precision Circuit Board & Overload Protection: With over load protection, quickly test voltage, shielding interference & continuity test can be 30. Show "OL" on the LCD if overload.
- ❑ More Functions Selection: Test with reinforced insulation protection to ensure your life safety, with low battery indication, data hold, auto power off function and full symbol display clearly.
- ❑ Easy to Use & Clear to Read: Easy to operate, accurate readings, low power consumption, perfect home tool for the laboratory, home, factory, etc. Protected by rubber for drop protection.
- ❑ Portable Design: There is a back bracket for supporting multimeter, and also can collect test probe for your convenience. Backlight LCD for easy operation in dimly lit areas.

Function	Range	Accuracy
		HT108L
DC Voltage	200mV/2V/20V/200V/600V	±(1.0%+5)
AC Voltage	20V/200V/600V	±(1.0%+5)
DC Current	20mA/200mA	±(1.5%+5)
	10A	±(1.5%+5)
Resistance	200Ω/2kΩ/20kΩ/200kΩ/2MΩ/20MΩ	±(1.2%+5)
Display		2000 counts
Auto/Manual range		Manual
Diode test		✓
Continuity		✓
Data hold		✓
True RMS		✓
Low battery indication		✓
Auto power off		✓
Backlight		✓
Power		2x1.5V AAA Batteries
Weight		Approx.91g
Size		129x67x36mm
QTY		60pcs
Safety Rating		EN61010-1-2-030, EN61010-2-033, CATIII 600V

ติดต่อ บริษัท เนโอเนิกส์ จำกัด

27/85 ถนนสามวา แขวงมีนบุรี เขตมีนบุรี กรุงเทพฯ 10510

Tel: 061-8268939, 098-479-5684 E-mail: sale@tools.in.th Line ID: @neonics